Marshall CV620-WH4/BK4

Quick Installation Guide

1. Installation Using Ceiling or Wall Mount


1. Prepare parts and equipment required for installation


- Metal Plates A and B
- M3 Screws (8x Silver, 2x Black)

- Standard Mounting Hardware (Drill,
- Screwdriver, ladder, etc.)

1.2 Installation Steps

- 1. Adjust desired camera resolution using the DIP Switch setting prior to installation (refer to 2. DIP Switch Setting).
- 2. Attach Metal Plate A to camera base using supplied M3 screws (silver).





- З. Attach Metal Plate B to ceiling or wall using proper mounting hardware.
- Attach Camera (with Metal Plate A) to 4. Metal Plate B, and slide to the right to lock the plates in place.
- 5. Secure the installation with 2x M3 screws (silver), and one M3 (black) screw.

NOTE: Please be sure to use proper mounting hardware, and ensure that the mounting surface has obtained UL security approval.

SETTING OUTPUT MODE 0 1920X1080/60p 1 1920X1080/50p 2 1920X1080/30p 3 1920x1080/25p 4 1920x1080/60i 5 1920x1080/50i 6 1280x720/60p 7 1280x720/50p 8 1280x720/30p 9 1280x720/25p А 1080/59.94p В 1080/59.94i С 1080/29.97p D 720/59.94p Е 720/29.97p F Reserved



123





Notes



2. DIP Switch Setting

Output Switch



Marshall CV620-WH2/BK2 Quick Installation Guide